

Patent
09/905,568

LISTING OF CLAIMS

Please cancel Claims 1-3 and 46 without prejudice and without disclaimer of subject matter.

1. (Canceled)
2. (Canceled)
3. (Canceled)

4. (Original) A circuit for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for a first argument value x_1 and a second argument value x_2 , said circuit comprising:
a table storing a first data field including a plurality of table index values and a second data field including a plurality of computed table values corresponding to said plurality of table index values;

wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor.

5. (Original) The circuit of Claim 4, wherein said first argument value x_1 and a second argument value x_2 are not scaled by said first scaling factor.

6. (Original) The circuit of Claim 5, wherein said circuit computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by comparing said index value z to said plurality of table index values in said first data field of said table, determining a first one of said plurality of table index values to which said index value z corresponds, obtaining a first computed table value from said plurality of computed table values in said second data field associated with said first one of said plurality of table index values, and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

Patent
09/905,568

7. (Original) A circuit for decoding input data, comprising:
a decoder implementing the maximum a posteriori probability decoding algorithm, said decoder using a table for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ where x_1 and x_2 are first and second argument values, each derived from said input data, said table storing a first data field including a plurality of table index values and a second data field including a plurality of computed table values corresponding to said plurality of table index values;
wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor.
8. (Original) The circuit of Claim 7, wherein said first argument value x_1 and said second argument value x_2 are not scaled by said first scaling factor.
9. (Original) The circuit of Claim 7, wherein said decoder computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by obtaining a first computed value from said plurality of computed table values in said second data field of said table associated with a first table index value of said plurality of table index values in said first data field corresponding to said index value z , and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

Patent
09/905,568

10. (Original) The circuit of Claim 7 wherein said decoder computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by comparing said index value z to said plurality of table index values in said first data field of said table, determining a first one of said plurality of table index values to which said index value z corresponds, obtaining a first computed table value from said plurality of computed table values in said second data field associated with said first one of said plurality of table index values, and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

11. (Original) The circuit of Claim 7 wherein said table is stored in a memory unit in said decoder.

12. (Original) The circuit of Claim 7 wherein said table is stored in a logic circuit in said decoder.

13. (Original) The circuit of Claim 7 wherein said plurality of table index values are selected at regular intervals within said predefined range of $|x_1 - x_2|$ argument values.

14. (Original) The circuit of Claim 7 wherein said table has at most eight entries of said plurality of table index values and said plurality of computed table values.

15. (Original) The circuit of Claim 7 wherein said first scaling factor is the noise variance of said input data.

16. (Original) The circuit of Claim 15 wherein each of said plurality of table index values and each of said plurality of computed table values are multiplied by said noise variance.

Patent
09/905,568

17. (Original) The circuit of Claim 7 wherein said input data is quantized and said first scaling factor is a quantizer level value indicative of the first quantizer output level.
18. (Original) The circuit of Claim 17 wherein each of said plurality of table index values and each of said plurality of computed table values are divided by said quantizer level value.
19. (Original) The circuit of Claim 17, wherein said table further comprises a second scaling factor being a value for dynamic range and precision adjustment, and each of said plurality of table index values and each of said plurality of computed table values are scaled by said first and second scaling factor while said input data are scaled by said second scaling factor only.
20. (Original) The circuit of claim 19 wherein each of said plurality of table index values and each of said plurality of computed table values are multiplied by said second scaling factor.
21. (Original) The circuit of Claim 7 wherein said table further comprises a second scaling factor and said plurality of table index values and said plurality of computed table values are scaled by said first and second scaling factors.
22. (Original) The circuit of Claim 7 wherein said decoder implements the Log-MAP decoding algorithm.
23. (Original) The circuit of Claim 7 wherein said input data is punctured and said decoder comprises a depuncturing circuit for depuncturing said input data.

Patent
09/905,568

24. (Canceled) A method for generating a table, in a decoder applying the maximum a-posteriori probability algorithm for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for a first argument value x_1 and a second argument x_2 , the method for generating a table comprising:

- generating a first data field including a plurality of table index values being selected from a predefined range of $|x_1 - x_2|$ argument values;
- scaling said table index values by a first scaling factor;
- generating a second data field including a plurality of computed table values computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values; and
- scaling said computed table values by said first scaling factor.

25. (Original) The method of Claim 24, wherein said first argument value x_1 and said second argument value x_2 are not scaled by said first scaling factor.

26. (Original) The method of Claim 24, further comprising:

- computing an index value $z = |x_1 - x_2|$;
- obtaining a first computed table value from said plurality of computed table values in said second data field of said table associated with a first table index value of said plurality of said table index values in said first data field corresponding to said index value z ;
- determining a greater of said first argument value x_1 and said second argument value x_2 ; and
- adding said first computed table value to said greater of said first argument value x_1 and said second argument value x_2 .

Patent
09/905,568

27. (Original) The method of Claim 24, further comprising:
computing an index value $z = |x_1 - x_2|$;
comparing said index value z to said plurality of table index values in said data field of
said table;
determining a first one of said plurality of table index values to which said index value z
corresponds;
obtaining a first computed table value from said plurality of computed table values in said
second data field of said table associated with said first one of said plurality of table index
values;
determining a greater of said first argument value x_1 and said second argument value x_2 ;
and
adding said first computed table value to said greater of said first argument value x_1 , and
said second argument value x_2 .

28. (Original) The method of Claim 24, further comprising:
storing said table in a memory unit in said decoder.

29. (Original) The method of Claim 24, further comprising:
storing said table in a logic circuit in said decoder.

30. (Original) The method of Claim 24, wherein said plurality of table index
values are selected at regular intervals within said predefined range of $|x_1 - x_2|$ argument values.

31. (Original) The method of Claim 24, wherein said first scaling factor is the
noise variance of input data being decoded by said decoder.

**Patent
09/905,568**

32. (Original) The method of Claim 31, wherein said scaling of said table index values and said scaling of said computed table values comprise:

 multiplying said table index values by said first scaling factor; and
 multiplying said computed table values by said first scaling factor.

33. (Original) The method of Claim 24, wherein said first scaling factor is a quantizer level value indicative of the first quantizer output level of input data being decoded by said decoder.

34. (Original) The method of Claim 33, wherein said scaling of said table Index values and said scaling of said computed table values comprise:

 dividing said table index values by said first scaling factor; and
 dividing said computed table values by said first scaling factor.

35. (Original) The method of Claim 33, further comprising:
 scaling said table index values by a second scaling factor, said second factor being a value for dynamic range and precision adjustment;

 scaling said computed table values by said second scaling factor;
 scaling said first argument value x_1 and said second argument value x_2 by said second scaling factor only.

36. (Original) The method of Claim 35, wherein said scaling of said table index values and said scaling of said computed table values comprise:

 multiplying said table index values by said second scaling factor; and
 multiplying said computed table values by said second scaling factor.

Patent
09/905,568

37. (Original) The method of Claim 24, wherein said scaling of said table Index values and said scaling of said computed table values further comprise scaling by a second scaling factor.

38. (Previously Presented) The method of Claim 24, wherein said decoder implements the Log-Map decoding algorithm.

39. (Original) A circuit for decoding a frame of input data, comprising:
a decoder implementing the maximum a posteriori probability decoding algorithm, said decoder having an input terminal coupled to receive said frame of input data, a bit probabilities output terminal, and a bit decision output terminal, said decoder using a table for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ where x_1 and x_2 are first and second argument values, each derived from said input data, said table storing a first data field including a plurality of table index values and a second data field including a plurality of computed table values corresponding to said plurality of table index values;

wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor;

an interleaver for interleaving a posteriori information computed in said decoder;

a deinterleaver for deinterleaving a posteriori information computed in said decoder; and

a switch for selectively connecting said bit probabilities output terminal of said decoder to said interleaver or said deinterleaver.

40. (Original) The circuit of Claim 39, wherein said input data are not scaled by said first scaling factor.

Patent
09/905,568

41. (Original) The circuit of Claim 39, wherein said first scaling factor is the noise variance of said input data.

42. (Previously Presented) A turbo decoder coupled to receive, from a demodulator, a data stream being transmitted over a channel, said turbo decoder comprising:
a decoder implementing the maximum a posteriori probability decoding algorithm, said decoder using a table for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ where x_1 and x_2 are first and second argument values, each derived from said data stream, said table storing a first data field including a plurality of table index values and a second data field including a plurality of computed table values corresponding to said plurality of table index values;
wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor.

43. (Previously Presented) The decoder of claim 42 wherein said decoder computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by comparing index value z to said plurality of table index values in said first data field of said table, determining a first one of said plurality of table index values to which said index value z corresponds, obtaining a first computed table value from said plurality of computed table values in said second data field associated with said first one of said plurality of table index values, and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

44. (Currently Amended) The ~~circuit~~ decoder of claim 42 wherein said table is stored in a memory unit in said decoder

45. (Canceled)

Patent
09/905,568

46. (Canceled)

47. (Original) A circuit for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for a first argument value x_1 and a second argument value x_2 , said circuit comprising:

a table storing a first data field including a plurality of table index values and a second data field including a plurality of computed table values corresponding to said plurality of table index values;

wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor; and

wherein said circuit computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by comparing said index value z to said plurality of table index values in said first data field of said table, determining a first one of said plurality of table index values to which said index value z corresponds, obtaining a first computed table value from said plurality of computed table values in said second data field associated with said first one of said plurality of table index values, and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

Patent
09/905,568

48. (Original) A circuit for decoding input data, comprising:
a decoder implementing the maximum a posteriori probability decoding algorithm, said decoder using a table for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ where x_1 and x_2 are first and second argument values, each derived from said input data, said table storing a first data field including a plurality of table index values and a second data field including a plurality of compound table values corresponding to said plurality of table index values;

wherein said plurality of table index values are selected from a predefined range of $|x_1 - x_2|$ argument values and scaled by a first scaling factor; and said plurality of computed table values are computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values, and scaled by said first scaling factor; and

wherein said decoder computes the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for an index value $z = |x_1 - x_2|$ by obtaining a first computed value from said plurality of computed table values in said second data field of said table associated with a first table index value of said plurality of table index values in said first data field corresponding to said index value z , and adding said first computed table value to the greater of said first argument value x_1 and said second argument value x_2 .

Patent
09/905,568

49. (Previously Presented) A method for generating a table, in a decoder applying the maximum a-posteriori probability algorithm for computing the function $\log(e^{x_1} + e^{x_2})$ or $\ln(e^{x_1} + e^{x_2})$ for a first argument value x_1 and a second argument x_2 , the method for generating a table comprising:

generating a first data field including a plurality of table index values being selected from a predefined range of $|x_1 - x_2|$ argument values;

scaling said table index values by a first scaling factor;

generating a second data field including a plurality of computed table values computed based on the equation $\log(1 + e^{-|x_1 - x_2|})$ or $\ln(1 + e^{-|x_1 - x_2|})$ for each of said $|x_1 - x_2|$ argument values selected for said table index values;

scaling said computed table values by said first scaling factor;

computing an index value $z = |x_1 - x_2|$;

obtaining a first computed table value from said plurality of computed table values in said second data field of said table associated with a first table index value of said plurality of said table index values in said first data field corresponding to said index value z ;

determining a greater of said first argument value x_1 and said second argument value x_2 ;

and

adding said first computed table value to said greater of said first argument value x_1 and said second argument value x_2 .